



## Public Address & Communication System

### ITC MUSIC MIXER



#### Descriptions

The Three in One series BGM/Paging amplifiers combine 3 music sources with 5 zone amplifier together, which provides an economy solution for small PA applications where background music, zone paging and control is needed.

The amplifier also featured of built-in a weekly timer to easily enjoy the scheduled music system and school ring bell system through a remote control.

Ideal applications for super market, school, retail shop, bank, police station, villa, train and bus station, factory, theme salon, restaurant, hotel and hospital, etc.

#### Features

- Built-in CD player, MP3, AM/FM tuner and weekly timer
- Rated power from 60W, 120W, 240W to 350W
- 100V/70V line transformer-isolated speaker outputs and low impedance 4-16ohms speaker output
- With digital IR remote control to program on built-in weekly timer and manually select source to broadcast
- Built-in Mp3 player of SD card slot to read MP3 files, with play, stop and pause buttons
- Built-in FM/AM tuner with antenna, AM to FM switch, frequency selector and Auto/Manual operation switch, capacity of 50 channels storage
- Built-in CD player, which supports , VCD, CD, MP3 formats, play, stop and repeat keys (No video only audio)
- 5 zone 100V line speaker outputs
- MIC 1 with VOX priority over other inputs
- One extra aux input and aux output
- 5 inch LCD English display for weekly timer and program broadcasting
- MP3, Radio, CD, AUX, MIC separate volume control and bass treble tone control
- Select, down and up button in front panel
- Stand-by power function
- Protection: current limiter, short circuit and thermal protection circuits

#### Optional

- Panel with/without handhold



## Public Address & Communication System

### Specifications

Model	T-6601	T-6612	T-6624	T-6635
Rated Power Output	60W	120W	240W	350W
Speaker Outputs	70V,100V & 4 ~ 16Ω			
Sensitivity Input	0dB			
KD	400			
S/N Less than	85dB			
Frequency Response	80Hz ~ 15KHz, ±0.5dB			
Tone	Bass:±10dB at 100Hz Treble: ±10dB at 10KHz			
Tuner AM Channel	522KHz ~ 1622KHz			
AM Step	9KHz			
Tuner FM Channel	87MHz ~ 108MHz			
FM Step	50KHz			
Distortion	<0.6%			
Speed rate	70V/ms			
Cool Method	Fan Cool Way			
Indicator	Power, Signal, Leak, Protect, Overload			
Protection	Power On, Temp, Exceed, Overload, Short circuit			
Power Supply	~ 110V/60Hz or ~ 230V/50Hz			
PowerConsumption	160W	220W	340W	450W
Dimension	484x420x132mm			
Weight	14Kg	16.Kg	20.6Kg	21.8Kg